

Capcom 1942 Pinout

WWW.ARCANIAC.COM

1942			
Solder Side			Parts Side
Ground	A	1	Ground
+5 Volts	B	2	+5 Volts
+12 Volts	C	3	+12 Volts
Ground	D	4	Ground
Speaker -	E	5	Speaker -
Speaker +	F	6	Speaker +
Coin Counter -	H	7	Coin Counter +
Key	J	8	Key
P1 Shoot	K	9	P1 Up
P1 Down	L	10	P1 Left
P1 Right	M	11	P1 Ground
P2 Shoot	N	12	P2 Up
P2 Down	P	13	P2 Left
P2 Right	R	14	P2 Ground
P2 Start	S	15	Ground
P1 Start	T	16	Ground
Coin Switch	U	17	Ground
Service Switch	V	18	Ground
Not Used	W	19	P1 Loop
Not Used	X	20	P2 Loop
Not Used	Y	21	Video Ground
Video Sync	Z	22	Video Red
Video Green	a	23	Video Blue
Not Used	b	24	Not Used
Not Used	c	25	Not Used
Not Used	d	26	Not Used
+5 Volts	e	27	
Ground	f	28	Ground

Unique Pinout only used by 1942.