

SNK NEO-GEO MVS MULTI SLOTS PINOUT | INFO SHEET



WWW.ARCANIAC.COM

COMPATIBLE SYSTEMS

NEO-MVH MV 2 / 4 / 6

POWER SUPPLY REQUIREMENTS	
Current rating (Amps) Minimum	
+5 VOLTS	
+12 VOLTS	

SNK NEO-GEO MVS			
Solder Side	PIN #		Parts Side
GROUND	A	1	GROUND
GROUND	B	2	GROUND
+5 VOLTS	C	3	+5 VOLTS
+5 VOLTS	D	4	+5 VOLTS
NOT USED	E	5	NOT USED
+12 VOLTS	F	6	+12 VOLTS
KEY	H	7	KEY
COIN COUNTER 2	J	8	COIN COUNTER 1
COIN LOCK OUT 2	K	9	COIN LOCK OUT 1
SPEAKER (+) LEFT	L	10	SPEAKER (+) RIGHT
TEST SWITCH	M	11	AUDIO (+) MONO
VIDEO GREEN	N	12	VIDEO RED
VIDEO SYNC	P	13	VIDEO BLUE
SERVICE SWITCH	R	14	VIDEO GROUND
COIN SWITCH 4	S	15	COIN SWITCH 3
COIN SWITCH 2	T	16	COIN SWITCH 1
2P START	U	17	1P START
2P UP	V	18	1P UP
2P DOWN	W	19	1P DOWN
2P LEFT	X	20	1P LEFT
2P RIGHT	Y	21	1P RIGHT
2P BUTTON 1 (A)	Z	22	1P BUTTON 1 (A)
2P BUTTON 2 (B)	a	23	1P BUTTON 2 (B)
2P BUTTON 3 (C)	b	24	1P BUTTON 3 (C)
2P BUTTON 4 (D)	c	25	1P BUTTON 4 (D)
SELECT GAME DOWN	d	26	SELECT GAME UP
GROUND	e	27	GROUND
GROUND	f	28	GROUND