

TAITO CLASSIC "G"			
Solder Side			Parts Side
Ground	A	1	Ground
Video Ground	B	2	Video Red
Video Blue	C	3	Video Green
Not Used	D	4	Video Sync
Speaker -	E	5	Speaker +
Key	F	6	Key
Not Used	H	7	Not Used
Coin 2	J	8	Coin 1
Counter 2	K	9	Counter 1
Lockout Coil 2	L	10	Lockout Coil 1
Tilt / Slam Switch	M	11	Service Switch
P2 Start	N	12	P1 Start
P2 Up	P	13	P1 Up
P2 Down	R	14	P1 Down
P2 Right	S	15	P1 Right
P2 Left	T	16	P1 Left
Not Used	U	17	Not Used
Not Used	V	18	Not Used
Not Used	W	19	Not Used
Not Used	X	20	Not Used
P2 Button 1	Y	21	P1 Button 1
P2 Button 2	Z	22	P1 Button 2

TAITO CLASSIC "T" *			
Solder Side			Parts Side
Ground	A	1	Ground
Ground	B	2	Ground
Ground	C	3	Ground
Ground	D	4	Ground
Not Used	E	5	Not Used
Not Used	F	6	Not Used
Key	H	7	Key
Not Used	J	8	Not Used
Not Used	K	9	Not Used
Not Used	L	10	Not Used
Not Used	M	11	Not Used
Not Used	N	12	Not Used
Not Used	P	13	Not Used
Not Used	R	14	Not Used
+ 5 Volts	S	15	+ 5 Volts
+ 5 Volts	T	16	+ 5 Volts
+ 5 Volts	U	17	+ 5 Volts
+ 5 Volts	V	18	+ 5 Volts

TAITO CLASSIC "H"	
Ground	1
Ground	2
Ground	3
Ground	4
+5 Volts	5
+5 Volts	6
+5 Volts	7
- 5 Volts	8
+12 Volts	9
Key	10
+12 Volts	11
+12 Volts	12

*Connector T, is an extra power connector used on games that have a two boards stack. It is not required.

TAITO CLASSIC GAMES

TAITO CLASSIC

Alpine Ski
Bubble Bobble
Elevator Action
The Fairyland Story
Front Line
Jungle Hunt
Jungle King
Kram
Legend of Kage
LSA Squad
Return of the Invaders
Wild Western

TAITO ARKANOID

Arkanoid
Tournament Arkanoid

